

OMNITRONIC PM-322P 3-channel DJ Mixer with Bluetooth & USB Player Art. No.: 10006874

3-channel DJ mixer with Bluetooth and MP3 player

GTIN: 4026397653403









List price: 236.81 €

incl. 19% VAT.

Features:

- 3 input channels with gain control, 3-band equalizer, cue button and channel fader
- DJ microphone channel with level control and 2-band equalizer
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Crossfader with adjustable curve and reverse function
- Master channel with level control and 6-digit stereo LED level meter, switchable between master and PFL signal
- 6-digit stereo LED level meter
- 6 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Record output, independent of the master
- Control via Bluetooth
- LCD display
- Operating range up to 10m with line-of-sight
- Desktop console housing
- For application areas such as: Party room; mobile djs / entertainer; mobile use Package contents
- 1 x mixer, 1 x user manual, 1 x power cord, 1 x RCA cable, 1 x declaration of conformity

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	25 W
Protection class:	Protection class II

Logistic

EAN / GTIN: 4026397653403 Weight: 3,17 kg Length: 0.31 m Width: 0.31 m Heigth: 0.14 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Control:	Bluetooth
Bluetooth:	Version: 4,2 + EDR Profiles: A2DP, AVRCP
Bluetooth device name:	PM-322P
Audio player:	USB + Bluetooth
Range:	Range up to 10m with line-of-sight
Carrier frequency:	2,4 GHz
Housing color:	Black
Display type:	LCD display
Control elements:	Audio player, crossfader, cue mix function, source selector, crossfade curve switch; crossfade reverse switch
Status LED:	Switchable master level meter, clip, CUE, power
Connections:	Input: line via 4 x stereo RCA
	Input: line/phono via 2 x stereo RCA
	Input: audio player via 1 x USB A (F) mounting version
	Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version
	Output: master via 2 x 3-pin XLR
	Output: master via 2 x stereo RCA
	Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input chanel: 1 x stereo with line-line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Input chanel: 2 x stereo with line-line/phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Microphon chanal: 1 x mono via jack, channel control via rotary dial, 2-band tone control EQ, cue mix function
	Master output: 1 x stereo via XLR or RCA, channel control via rotary dial
	Headphones output: 1 x stereo via jack, channel control via rotary dial
Music format:	MP3, WAV; WMA
USB port:	Туре А
Housing design:	Desktop console housing
Dimensions:	Length: 28,3 cm
	Width: 23 cm
	Height: 10,7 cm
Weight:	2,58 kg
Audio player	
Available storage media:	USB devices max. 32GB (FAT 32)