

## **OMNITRONIC PM-311P DJ Mixer with Player**

3-channel DJ mixer with integrated MP3 player









# List price: 148.75 €

incl. 19% VAT.

#### Features:

- 3 input channels, switchable 2 x phono/line and 1 x USB/line
- All input channels with gain control, 3-band equalizer and cue button
- DJ microphone input with talkover selector, level control and 3-band equalizer
- Pre-fader listening (CUE) to the input channels and the master output via adjustable headphones output, with cue mix control
- Crossfader for crossfading between the phono/line channels
- 5-digit stereo LED level meter, switchable between master and PFL signal
- Additional recording output
- Desktop console housing
- For application areas such as: Party room; mobile djs / entertainer; mobile use Package contents
- 1 x mixer, 1 x user manual, 1 x external mains adapter

### **Technical specifications:**

Power supply:	230 V AC, 50 Hz 12V
Power consumption:	4,00 W
Protection class:	Protection class III
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Frequency range:	20 - 20000 Hz

#### Logistic

EAN / GTIN: 4026397696578 Weight: 2,13 kg Length: 0.34 m Width: 0.24 m Heigth: 0.12 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

S/N ratio:	>75 dB
THD:	<0,07 % at 1 kHz
Audio player:	USB
Housing color:	Black
Control elements:	Crossfader, source selector, talkover, power switch
Status LED:	Switchable master level meter, chanal source, CUE, ON AIR
Connections:	Input: line/phono via 2 x stereo RCA
	Input: line via 1 x stereo RCA
	Input: audio player via 1 x USB A (F) mounting version
	Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version
	Output: master via 1 x stereo RCA
	Output: rec. via 1 x stereo RCA
	Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input chanel: 2 x stereo with line-phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch, source selector, CUE switch
	Input chanel: 1 x stereo with line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch
	Microphon chanal: 1 x mono via jack, channel control via rotary dial, 2-band tone control EQ, ON AIR switch
	Master output: 1 x stereo via RCA, channel control via rotary dial, cue mix function
	Headphones output: 1 x stereo via jack, channel control via rotary dial
Music format:	MP3, WAV
Available storage media:	USB devices max. 32GB (FAT 32)
USB port:	Туре А
Housing design:	Desktop console housing
Dimensions:	Width: 17,2 cm
	Depth: 26 cm
	Height: 7,8 cm